



Item no. 324/062
Manufacturer's no. 60693

Built-In Charger USB-A | USB-C 18 W

wentronic
SOLUTIONS

Information

Dimensions	44.5x36 mm
Pack size	20x 14.9x3.9 cm
Net weight	30 g
Gross weight	40 g
Catalogue page	565

Always have a full battery. The dual USB-A and USB-C socket can be installed in no time as a convenient charging station in motorhomes, caravans and boats.

It charges numerous mobile devices such as smartphones, tablets or cameras and displays the on-board voltage during charging. When the battery is 90% full, the display switches off automatically.

- With USB-A and USB-C connection for quick and easy charging
- Charges popular smartphones at high speed with Quick Charge and Power Delivery
- Easy to install and compatible with the Berker and Inprojal switch ranges
- Suitable for wall thicknesses up to 17 mm
- Safe due to rounded edges
- Protection against short circuits, overvoltage and high temperatures
- With open cable covers and 150 mm cable
- Incl. 7-segment LED display for on-board voltage

Specifications

Connection	USB-A USB-C
Installation depth	44.5 mm
Colour	black
Inner ø	27 mm
Cable length	150 mm
Material	plastic
Nominal capacity	18 W
Nominal voltage	12 V 24 V
Nominal current	7 mA
Type	USB-A USB-C